SPEC® MPIM2007 Result

Copyright 2006-2010 Standard Performance Evaluation Corporation

Intel Corporation

Endeavor (Intel Xeon E5-2697 v2, 2.70 GHz,
DDR3-1866 MHz, SMT on, Turbo off)

SPECmpiM_peak2007 = Not Run

SPECmpiM_base2007 = 6.33

MPI2007 license: 13
Test sponsor: Intel Corporation
Tested by: Pavel Shelepugin

Test date: Aug-2013
Hardware Availability: Sep-2013
Software Availability: Sep-2013



Results Table

Benchmark	Base							Peak						
	Ranks	Seconds	Ratio	Seconds	Ratio	Seconds	Ratio	Ranks	Seconds	Ratio	Seconds	Ratio	Seconds	Ratio
104.milc	24	333	4.71	333	4.70	**333**	**4.71**							
107.leslie3d	24	**878**	**5.94**	881	5.92	878	5.95							
113.GemsFDTD	24	789	8.00	787	8.01	**788**	**8.01**							
115.fds4	24	307	6.35	**290**	**6.72**	290	6.74							
121.pop2	24	526	7.84	507	8.14	**519**	**7.95**							
122.tachyon	24	634	4.41	637	4.39	**635**	**4.40**							
126.lammps	24	722	4.04	722	4.04	**722**	**4.04**							
127.wrf2	24	**782**	**9.97**	782	9.97	783	9.96							
128.GAPgeofem	24	**312**	**6.62**	312	6.62	312	6.61							
129.tera_tf	24	569	4.87	562	4.93	**563**	**4.92**							

Table continues on next page. Results appear in the order in which they were run. Bold underlined text indicates a median measurement.

SPEC MPIM2007 Result

Copyright 2006-2010 Standard Performance Evaluation Corporation

Intel Corporation

Endeavor (Intel Xeon E5-2697 v2, 2.70 GHz, DDR3-1866 MHz, SMT on, Turbo off)

SPECmpiM_peak2007 = Not Run

SPECmpiM_base2007 = 6.33

MPI2007 license: 13
Test sponsor: Intel Corporation
Tested by: Pavel Shelepugin

Test date: Aug-2013
Hardware Availability: Sep-2013
Software Availability: Sep-2013

Results Table (Continued)

Benchmark	Base							Peak						
	Ranks	Seconds	Ratio	Seconds	Ratio	Seconds	Ratio	Ranks	Seconds	Ratio	Seconds	Ratio	Seconds	Ratio
130.socorro	24	264	14.4	**263**	**14.5**	263	14.5							
132.zeusmp2	24	**498**	**6.24**	497	6.24	499	6.21							
137.lu	24	879	4.18	**883**	**4.16**	888	4.14							

Results appear in the order in which they were run. Bold underlined text indicates a median measurement.

Hardware Summary

Type of System:	Homogeneous
Compute Node:	Endeavor Node
Interconnects:	IB Switch Gigabit Ethernet
File Server Node:	NFS
Total Compute Nodes:	1
Total Chips:	2
Total Cores:	24
Total Threads:	48
Total Memory:	64 GB
Base Ranks Run:	24
Minimum Peak Ranks:	--
Maximum Peak Ranks:	--

Software Summary

C Compiler:	Intel C++ Composer XE 2013 for Linux, Version 14.0.0.080 Build 20130728
C++ Compiler:	Intel C++ Composer XE 2013 for Linux, Version 14.0.0.080 Build 20130728
Fortran Compiler:	Intel Fortran Composer XE 2013 for Linux, Version 14.0.0.080 Build 20130728
Base Pointers:	64-bit
Peak Pointers:	64-bit
MPI Library:	Intel MPI Library 4.1.1.036 for Linux
Other MPI Info:	None
Pre-processors:	No
Other Software:	None

Node Description: Endeavor Node

Hardware

Number of nodes:	1
Uses of the node:	compute
Vendor:	Intel
Model:	R2208GZ4GC
CPU Name:	Intel Xeon E5-2697 v2
CPU(s) orderable:	1-2 chips
Chips enabled:	2
Cores enabled:	24
Cores per chip:	12
Threads per core:	2
CPU Characteristics:	Intel Turbo Boost Technology disabled, 8.0 GT/s QPI, Hyper-Threading enabled
CPU MHz:	2700
Primary Cache:	32 KB I + 32 KB D on chip per core
Secondary Cache:	256 KB I+D on chip per core
L3 Cache:	30 MB I+D on chip per chip, 30 MB shared / 12 cores
Other Cache:	None
Memory:	64 GB (8 x 8 GB 2Rx4 PC3-14900R-13, ECC)
Disk Subsystem:	Seagate 600 GB SSD ST9600205SS
Other Hardware:	None
Adapter:	Intel (ESB2) 82575EB Dual-Port Gigabit Ethernet Controller
Number of Adapters:	1

Continued on next page

Software

Adapter:	Intel (ESB2) 82575EB Dual-Port Gigabit Ethernet Controller
Adapter Driver:	e1000
Adapter Firmware:	None
Adapter:	Mellanox MCX353A-FCAT ConnectX-3
Adapter Driver:	OFED 1.5.3.1
Adapter Firmware:	2.10.0
Operating System:	Red Hat EL 6.1, kernel 2.6.32-131
Local File System:	Linux/ext2
Shared File System:	NFS
System State:	Multi-User
Other Software:	Platform LSF 8.0

SPEC MPIM2007 Result

Copyright 2006-2010 Standard Performance Evaluation Corporation

Intel Corporation

Endeavor (Intel Xeon E5-2697 v2, 2.70 GHz, DDR3-1866 MHz, SMT on, Turbo off)

SPECmpiM_peak2007 = Not Run

SPECmpiM_base2007 = 6.33

MPI2007 license: 13
Test sponsor: Intel Corporation
Tested by: Pavel Shelepugin

Test date: Aug-2013
Hardware Availability: Sep-2013
Software Availability: Sep-2013

Node Description: Endeavor Node

Slot Type:	PCI-Express x8
Data Rate:	1Gbps Ethernet
Ports Used:	2
Interconnect Type:	Ethernet
Adapter:	Mellanox MCX353A-FCAT ConnectX-3
Number of Adapters:	1
Slot Type:	PCIe x8 Gen3
Data Rate:	InfiniBand 4x FDR
Ports Used:	1
Interconnect Type:	InfiniBand

Node Description: NFS

Hardware

Number of nodes:	1
Uses of the node:	fileserver
Vendor:	Intel
Model:	S7000FC4UR
CPU Name:	Intel Xeon CPU
CPU(s) orderable:	1-4 chips
Chips enabled:	4
Cores enabled:	16
Cores per chip:	4
Threads per core:	2
CPU Characteristics:	--
CPU MHz:	2926
Primary Cache:	32 KB I + 32 KB D on chip per core
Secondary Cache:	8 MB I+D on chip per chip, 4 MB shared / 2 cores
L3 Cache:	None
Other Cache:	None
Memory:	64 GB
Disk Subsystem:	8 disks, 500GB/disk, 2.7TB total
Other Hardware:	None
Adapter:	Intel 82563GB Dual-Port Gigabit Ethernet Controller
Number of Adapters:	1
Slot Type:	PCI-Express x8
Data Rate:	1Gbps Ethernet
Ports Used:	1
Interconnect Type:	Ethernet

Software

Adapter:	Intel 82563GB Dual-Port Gigabit Ethernet Controller
Adapter Driver:	e1000e
Adapter Firmware:	N/A
Operating System:	RedHat EL 5 Update 4
Local File System:	None
Shared File System:	NFS
System State:	Multi-User
Other Software:	None

Interconnect Description: IB Switch

Hardware		Software
Vendor:	Mellanox	
Model:	Mellanox MSX6025F-1BFR	
Switch Model:	Mellanox MSX6025F-1BFR	
Number of Switches:	46	
Number of Ports:	36	
Data Rate:	InfiniBand 4x FDR	
Firmware:	7.2.0	
Topology:	Fat tree	
Primary Use:	MPI traffic	

Interconnect Description: Gigabit Ethernet

Hardware		Software
Vendor:	Force10 Networks	
Model:	Force10 S50, Force10 C300	
Switch Model:	Force10 S50, Force10 C300	
Number of Switches:	15	
Number of Ports:	48	
Data Rate:	1Gbps Ethernet, 10Gbps Ethernet	
Firmware:	8.2.1.0	
Topology:	Fat tree	
Primary Use:	Cluster File System	

Submit Notes

```
The config file option 'submit' was used.
```

General Notes

```
130.socorro (base): "nullify_ptrs" src.alt was used.

 MPI startup command:
   mpiexec.hydra command was used to start MPI jobs.

 BIOS settings:
   Intel Hyper-Threading Technology (SMT): Enabled (default is Enabled)
   Intel Turbo Boost Technology (Turbo)  : Disabled (default is Enabled)

 RAM configuration:
   Compute nodes have 2x8-GB RDIMM on each memory channel.

 Network:
   Forty six 36-port switches: 18 core switches and 28 leaf switches.
   Each leaf has one link to each core. Remaining 18 ports on 25 of 28 leafs
   are used for compute nodes. On the remaining 3 leafs the ports are used
```

Continued on next page

General Notes (Continued)

```
    for FS nodes and other peripherals.

  Job placement:
    Each MPI job was assigned to a topologically compact set of nodes, i.e.
    the minimal needed number of leaf switches was used for each job: 1 switch
    for 24/48/96/192/384 ranks, 2 switches for 768 ranks, 4 switches for 1536 ranks,
    8 switches for 3072 ranks.

  Platform LSF was used for job submission. It has no impact on performance.
    Information can be found at: http://www.platform.com
```

Base Compiler Invocation

C benchmarks:
`mpiicc`

C++ benchmarks:

126.lammps: `mpiicpc`

Fortran benchmarks:
`mpiifort`

Benchmarks using both Fortran and C:
`mpiicc mpiifort`

Base Portability Flags

121.pop2: `-DSPEC_MPI_CASE_FLAG`
126.lammps: `-DMPICH_IGNORE_CXX_SEEK`
127.wrf2: `-DSPEC_MPI_CASE_FLAG -DSPEC_MPI_LINUX`
130.socorro: `-assume nostd_intent_in`

Base Optimization Flags

C benchmarks:
`-O3 -xCORE-AVX-I -no-prec-div`

C++ benchmarks:

126.lammps: `-O3 -xCORE-AVX-I -no-prec-div`

Fortran benchmarks:
`-O3 -xCORE-AVX-I -no-prec-div`

Continued on next page

Base Optimization Flags (Continued)

Benchmarks using both Fortran and C:
`-O3 -xCORE-AVX-I -no-prec-div`

The flags file that was used to format this result can be browsed at
`http://www.spec.org/mpi2007/flags/EM64T_Intel140_flags.html`

You can also download the XML flags source by saving the following link:
`http://www.spec.org/mpi2007/flags/EM64T_Intel140_flags.xml`

SPEC and SPEC MPI are registered trademarks of the Standard Performance Evaluation Corporation. All other brand and product names appearing in this result are trademarks or registered trademarks of their respective holders.

For questions about this result, please contact the tester.
For other inquiries, please contact webmaster@spec.org.

Tested with SPEC MPI2007 v2.0.1.
Report generated on Tue Jul 22 13:46:47 2014 by SPEC MPI2007 PS/PDF formatter v1463.
Originally published on 10 September 2013.