



CFP2000 Result

Copyright ©1999-2005, Standard Performance Evaluation Corporation

Advanced Micro Devices
TYAN Tomcat K8E (S2865), AMD Opteron (TM) 154

SPECfp2000 = 2191
SPECfp_base2000 = 1976

SPEC license #: 49 Tested by: Michael Paton Test date: Dec-2005 Hardware Avail: Jul-2005 Software Avail: Nov-2005

Benchmark	Reference Time	Base Runtime	Base Ratio	Runtime	Ratio	1000 2000 3000 4000			
168.wupwise	1600	56.4	2838	49.1	3261	[Bar chart showing ratio 3261]			
171.swim	3100	138	2253	133	2326	[Bar chart showing ratio 2326]			
172.mgrid	1800	104	1723	96.8	1859	[Bar chart showing ratio 1859]			
173.applu	2100	99.0	2122	85.8	2448	[Bar chart showing ratio 2448]			
177.mesa	1400	76.1	1840	57.8	2423	[Bar chart showing ratio 2423]			
178.galgel	2900	90.0	3222	80.7	3596	[Bar chart showing ratio 3596]			
179.art	2600	98.5	2639	68.3	3805	[Bar chart showing ratio 3805]			
183.earth	1300	76.2	1706	69.2	1880	[Bar chart showing ratio 1880]			
187.facerec	1900	71.4	2661	71.8	2647	[Bar chart showing ratio 2647]			
188.amp	2200	134	1641	125	1755	[Bar chart showing ratio 1755]			
189.lucas	2000	108	1849	102	1963	[Bar chart showing ratio 1963]			
191.fma3d	2100	123	1713	122	1720	[Bar chart showing ratio 1720]			
200.sixtrack	1100	117	939	112	979	[Bar chart showing ratio 979]			
301.apsi	2600	152	1711	146	1781	[Bar chart showing ratio 1781]			

Hardware

CPU: AMD Opteron (TM) 154 (939 pin)
CPU MHz: 2800
FPU: Integrated
CPU(s) enabled: 1 core, 1 chip, 1 core/chip
CPU(s) orderable: 1
Parallel: No
Primary Cache: 64KBI + 64KBD on chip
Secondary Cache: 1024KB (I+D) on chip
L3 Cache: N/A
Other Cache: N/A
Memory: 2x512MB, DDR400 CL2
Disk Subsystem: IDE, 160 GB
Other Hardware: None

Software

Operating System: SuSE Linux Enterprise Server 9 for AMD64
Compiler: PathScale EKOPath(TM) Compiler Suite, Release 2.3
File System: Linux/ext3
System State: Multi-user, run level 3

Notes/Tuning Information

Tested by Advanced Micro Devices

```
+FDO: PASS1= -fb_create fbdata PASS2= -fb_opt fbdata
+ACML means -L<acml2.7.0-install-dir>/pathscale64/lib -lacml,
which causes linking with AMD Core Math Library V2.7.0
```

Baseline optimization

```
C programs: -Ofast -WOPT:mem_opnds=on +FDO
Fortran programs: -Ofast -LNO:fusion=2 -OPT:fast_complex=on +FDO
Portability Flags:
178.galgel: -fixedform
```

Peak Tuning:

```
168.wupwise: -Ofast -LNO:prefetch Ahead=5:prefetch=3
-OPT:unroll_times_max=8:unroll_size=128:IEEE_NaN_Inf=off:ro=3
-IPA:linear=on:plimit=50000:callee_limit=5000
-INLINE:aggressive=on
```



CFP2000 Result

Copyright ©1999-2005, Standard Performance Evaluation Corporation

Advanced Micro Devices
TYAN Tomcat K8E (S2865), AMD Opteron (TM) 154

SPECfp2000 = 2191
SPECfp_base2000 = 1976

SPEC license #: 49 | Tested by: Michael Paton | Test date: Dec-2005 | Hardware Avail: Jul-2005 | Software Avail: Nov-2005

Notes/Tuning Information (Continued)

```

171.swim: -Ofast -CG:local_fwd_sched=on -LNO:fusion=2 -m3dnow
172.mgrid: -Ofast -CG:gcm=off -OPT:IEEE_arith=3:unroll_size=200
          -LNO:fusion=2:fission=1:blocking=off:prefetch_ahead=2
          -WOPT:mem_opnds=on:aggstr=0
173.applu: -Ofast -CG:local_fwd_sched=on -OPT:ro=3 -TENV:X=3
          -LNO:fusion=2:fission=2:full_unroll_size=10000:prefetch=3 +FDO
177.mesa: -O2 -ipa -OPT:Ofast -fno-math-errno -CG:local_fwd_sched=on -WOPT:mem_opnds=on +FDO
178.galgel: -Ofast -OPT:fast_complex=on +ACML +FDO
          RM_SOURCES=lapak.f90
179.art: -O3 -OPT:Ofast -fno-math-errno -mno-sse2 -m32
183.quake: -Ofast -CG:load_exe=2 -WOPT:mem_opnds=on -m32 +FDO
187.facerec: -Ofast -LNO:fusion=2
          -OPT:fast_complex=on:IEEE_NaN_Inf=off:unroll_size=0 +FDO
188.ammp: -O3 -OPT:alias=disjoint:unroll_times_max=8:Ofast:ro=3
          -fno-math-errno -TENV:X=4 +FDO
189.lucas: -Ofast -OPT:ro=3:fast_nint=off:unroll_size=256 -WOPT:mem_opnds=on +FDO
191.fma3d: -O2 -ipa -CG:load_exe=1 -OPT:Ofast:IEEE_arith=3:ro=3
          -WOPT:mem_opnds=on:retype_expr=on -IPA:pu_reorder=1 +FDO
200.sixtrack: -O3 -OPT:Ofast:Olimit=6000:early_intrinsics=on
          -fno-math-errno -CG:load_exe=1 +FDO
301.apsi: -Ofast -CG:load_exe=0 -LNO:prefetch=0:simd=2

```

Corsair CMX512-3200XL memory used in Dual Channel configuration
Memory timings manually set in BIOS: CAS=2, Trcd=2, Tras=5, Trp=2
BIOS rev 3.01

The tested system can be assembled using a standard ATX case and an Antec True 550
watt EPS12V Power Supply